

## AC LEAKAGE CURRENT TESTER

## TECHNICAL DATA

### FEATURES

- 10 $\mu$ A resolution
- Large 3-3/4 (4000-count) LCD
- Shielded transformer jaws open to 1.2"
- Max/Min and Data hold
- Overload protection
- Auto power-off
- Supplied with **TL-88-1** test leads, **AM-4** "AAA" batteries and **C-820** soft carrying case

### SPECIFICATIONS

**Current Range:** 40mA to 100A AC

**Resolution:** 10 $\mu$ A to 100mA AC

**Accuracy:**  $\pm(1.0\% + 3 \text{ digits})$

**Voltage Range:** 400 VAC

**Resolution:** 0.1 VAC

**Accuracy:**  $\pm(1.5\% + 10 \text{ digits})$

**Resistance Range:** 40 to 400 $\Omega$

**Resolution:** 0.1 $\Omega$

**Accuracy:**  $\pm(1.0\% + 2 \text{ digits})$

**Continuity Test:** 40 $\Omega$  threshold, beeper at 2.5kHz

**Dimensions:** 209 x 43 x 30mm

**Weight:** 200g

### ORDERING INFORMATION

ST-9809 ..... AC Leakage Current Tester

FC-300 ..... Fused Test Lead Set

ST-9809-NIST ..... Current Tester & NIST

